

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

| | |
|--------------|----------------------|
| Bulletin No. | 491Ø-17 |
| Description | TRSDOS |
| Model | Model II |
| Stock No. | 26-491Ø Version 2.Øa |
| Date | Dec. 16, 1981 |
| Page 1 of | 1 |

Problem

These patches are to change the operation of the HOST function from serial channel A to serial channel B on a permanent basis. Do not apply these patches unless you have a special situation which requires the use of the HOST function on channel B only. Please note that you should not try to use a serial printer (which also uses serial channel B) once these patches have been applied. If you attempt to do so, bytes will be intermixed on channel B.

Solution

PATCH SYSTEM64 R=24 B=53 F=3E64 C=3E65 (ALSO VALID FOR SYSTEM 32 IF 32K)

PATCH SYSTEM64 R=24 B=98 F=3E61 C=3E63 (ALSO VALID FOR SYSTEM 32 IF 32K)

PATCH SYSTEM64 R=25 B=65 F=1115ØØ C=1117ØØ (ALSO VALID FOR SYSTEM 32 IF 32K)

PATCH SYSTEM/SYS R=1Ø7 B=2Ø5 F=41 C=42

PATCH SYSTEM/SYS R=1Ø7 B=214 F=CB5E28E1CB9EØ66Ø C=CB5628E1CB96Ø662

PATCH SYSTEM/SYS R=1Ø7 B=231 F=Ø664 C=Ø665

PATCH SYSTEM/SYS R=1Ø7 B=239 F=42 C=41

PATCH SYSTEM/SYS R=1Ø7 B=242 F=CB5628C5CB96Ø662 C=CB5E28C5CB9EØ66Ø

PATCH SYSTEM/SYS R=1Ø8 B=3 F=Ø665 C=Ø664

PATCH SYSTEM/SYS R=61 B=141 F=CB5E C=CB56

PATCH SYSTEM/SYS R=62 B=3 F=41 C=42