



Model HR12A
FCC Approved

NEW!

Wireless

Palm Pad Remote Control

- **Controls up to 16 lights and appliances by remote control.**
- **Works with any X-10 Transceiver (RR501/TM751) or any X-10 Security System, and X-10 Modules.**
- **Works with the X-10 ActiveHome Two-Way Computer Interface to initiate Macros.**
- **Up to 100 ft. range.**

Palm Pad Remote Control Set Up and Operating Instructions

The HR12A Palm Pad Remote Control sends Wireless Radio Frequency (RF) signals to an X-10 Transceiver (RR501 or TM751) or any X-10 security system base receiver. The receiver then passes the signals onto your house wiring to control lights or appliances around your home. You plug lights and appliances into X-10 Modules (sold separately). The Palm Pad also works with the CM11A Two-Way Computer Interface to initiate macros (routines) so you can set up a "coming home" routine which is initiated when you press a button on the Palm Pad.

1. Install 4 AAA alkaline batteries (sold separately) in the Palm Pad's battery compartment.
2. Use a dime to set the Housecode dial to match the X-10 Modules and Transceiver you want to control.
3. Plug in an X-10 Transceiver (RR501 or TM751, sold separately).
4. Set the Palm Pad's slide switch to 1-8 to control X-10 Modules set to Unit Codes 1 thru 8.
5. Set the slide switch to 9-16 to control X-10 Modules 9 thru 16.
6. Press the corresponding ON or OFF button to turn X-10 Modules on and off.
7. To brighten or dim lights connected to X-10 Lamp Modules and Wall Switch Modules, first press the corresponding number button, then press the UP or DOWN (blue) buttons.

F.C.C. CAUTION - THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES. OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITIONS: (1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND (2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED, INCLUDING INTERFERENCE THAT MAY CAUSE UNDESIRED OPERATION.

NOTE: NO CHANGES OR MODIFICATIONS MAY BE MADE TO THE UNITS. ANY CHANGES MADE TO THE UNITS WILL VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

X-10 (USA) INC. LIMITED 1-YEAR WARRANTY

X-10 (USA) Inc. warrants X-10 products to be free from defective material and workmanship for a period of one (1) year from the original date of purchase at retail. X-10 (USA) Inc. agrees to repair or replace, at it's sole discretion, a defective X-10 product if returned to X-10 (USA) Inc. within the warranty period and with proof of purchase.

If service is required under this warranty:

1. Return the defective unit postage prepaid to X-10 (USA) Inc. at the address below.
2. Enclose a check for \$4.00 to cover postage and handling.
3. Enclose a dated proof of purchase.
4. X-10 is not responsible for shipping damage.

X-10 (USA) Inc.
91 Ruckman Rd.,
Closter, NJ 07624.
<http://www.x10.com>
Made in China