

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	1604-2
Description	Versafiles
Model	Model I
Stock No.	26-1604 Version 1.0
Date	October 31, 1980
Page 1 of	1

### Problem

In Model I VERSAFILES, a subscript out of range error or BS error can occur.

### Solution

The problem can be corrected by following the steps listed below.

1. Backup the diskette(s) and make the changes on the backup copy of the program.
2. In BASIC load the program by typing LOAD"VERSA".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of your owners manual)

Old Line: 110 CLEAR8000

New Line: 110 CLEAR 13000

Old Line: 120 DEFSTRA, B, C, D, E, F, K: DEFSNGL, X, Y, Z: DIME(80), Y(80), A(25)

New Line: 120 DEFSTRA, B, C, D, E, F, K: DEFINTL, X, Y, Z: DIME(200), Y(200),  
A(25), K(25)

4. Type SAVE"VERSA" to save the changes in the program.
5. At TRSDOS Ready, make a BACKUP copy of the corrected diskette.