

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4512-Ø4
Description	PROFILES II
Model	Model II
Stock No.	26-4512 Version 1.Ø
Date	Nov. 16, 1981
Page 1 of	1

Problem

It's been reported that Profiles II doesn't work with a serial printer properly.

Solution

1. At TRSDOS READY apply the following patches to a backup copy of your Profiles II diskette.

PATCH CLERK/EFC A=3411,F=3E64,C=3E7E

PATCH CLERK/EFC A=4F11,F=Ø664,C=Ø67E

PATCH CLERK/EFC A=4F2Ø,F=Ø665,C=Ø67D

PATCH CLERK/EFC A=56BC,F=Ø664,C=Ø67E

PATCH CLERK/EFC A=56C3,F=Ø665,C=Ø67D

PATCH CLERK/EFC A=5D66,F=ØEØØ,C=ØE42

*** After applying these patches, you should be able to use a serial printer with Profiles II.