

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 4530-06 _____
Description SCRIPSIT _____
Model Model II _____
Stock No. 26-4530 Version 1.0 _____
Date Nov. 16, 1981 _____
Page 1 of 1 _____

Problem

To circumvent widow line handling during repagination.

Solution

1. Reset the system at swap diskettes.
2. Answer the Date Prompt.
3. Press HOLD and press <ENTER> for the Time Prompt.
4. Type in the following patch.

```
PATCH SCRIPSIT/6 A=E3B3 F=C5 C=C9
```

5. Type STARTUP and press <ENTER>.
6. SCRIPSIT is now patched and you can continue operation.
7. Make a copy of the corrected diskette.