

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	491Ø-24
Description	TRSDOS
Model	Model II
Stock No.	26-491Ø Version 2.Øa
Date	Feb. 12, 1982
Page 1 of	1

Problem

The communications module COMSUB uses serial channel A per its definition. Some user, however, would like to be able to use COMSUB to communicate with a device (like the multi-pen plotter, for example) attached to serial channel B.

In order to get COMSUB to use serial channel B, the following optional patches should be applied to COMSUB.

Solution

(Optional patches for 64K version of COMSUB)

PATCH COMSUB64 A=EF8B F=3E6Ø C=3E62

PATCH COMSUB64 A=EF9A F=3E61 C=3E63