

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	6105-07
Description	TRSDOS 16
Model	Model II/16
Stock No.	26-6105 Version 4.1
Date	July 13, 1982
Page 1 of	1

Problem

These patches are used to permanently change the operation of the TERMINAL program to use channel B in place of channel A. Do not apply these patches unless you have a special situation which requires the use of channel B only. Please note that a serial printer (which also uses channel B) may not be used concurrently with TERMINAL once these patches are applied.

* * * THESE PATCHES ARE OPTIONAL! * * *

Solution

```
PATCH TERMINAL {R=5 B=172 F=3E61 C=3E63}
PATCH TERMINAL {R=5 B=248 F=3E60 C=3E62}
PATCH TERMINAL {R=6 B=164 F=3E64 C=3E65}
PATCH TERMINAL {R=6 B=173 F=3E64 C=3E65}
PATCH TERMINAL {R=6 B=183 F=3E64 C=3E65}
PATCH TERMINAL {R=6 B=193 F=3E61 C=3E63}
PATCH TERMINAL {R=6 B=251 F=3E60 C=3E62}
PATCH TERMINAL {R=8 B=37 F=3E60 C=3E62}
PATCH TERMINAL {R=8 B=86 F=3E60 C=3E62}
```