
-		REVISIONS		1	
LTR	DASH NO.	DESCRIPTION	DATE	APPROVED	
ΧI	9001	LID RLSE PER LRA 0076	Z DEC	15	
X2	9001	REV PER LRC 0392	708093	6 7 60	

# RESTRICTED RELEASE

JUN 1 2 1984



		<b>8</b>	DWG APPROVAL DATE		CENTRONICS				
11		<b>S M S</b>	DWN BOUTIN 29NOVEZ		data computer corp.				
	8		CHK DO RIDEC BZ		HUDSON, NEW HAMPSHIRE U.S.A.				
	SED	Z DE S	DR MGR AMP Onorth	TITLE	ENGINEERING PRODUCT SPECIFICATION				
	7	AT STEE	DES ENG Coff Wong	STOR	ENGINEERING PRODUCT SPECIFICATION RED ENERGY 18 WIRE				
	<u> </u>	3 28 58	Q S						
١,		NO N		LINE PRINT HEAD					
	<u></u>	2 5 5 5 5							
	SS		DWG RELEASE DATE	SIZE	NUMBER	v			
MEXT	E	E TO Y	ENG PROG MGR	ΑΙ	1 8000 2195 IX	2			
	NE NE		MFG ENG	SCALE	10000213311				
11		E E E E	QA	30,000	DO NOT SCALE PRINT SHEET OF	-			

KEF 3/78

### -ENGINEERING PRODUCT SPECIFICATION-

### **CENTRONICS**°

SPEC. NO. 80002195-9001

REV X2

DATE November 30, 1983

PAGE 2 OF 8

	TABLE OF CONTENTS	PAGE
1.0	GENERAL DESCRIPTION	3
2.0	RELATED DOCUMENTS	3
3.0	PRINT HEAD CHARACTERISTICS AND PERFORMANCE	3
3.1	PRINT HEAD CHARACTERISTICS	3
3.2	PRINT HEAD PERFORMANCE	4
4.0	PRINT HEAD OVERALL SIZE AND WEIGHT	4
5.0	TEST EQUIPMENT OPERATION	5
6.0	SERVICE REQUIREMENTS	5
7.0	ENVIRONMENTAL REQUIREMENTS	5
7.1	OPERATING ENVIRONMENT	5
7.2	STORAGE ENVIRONMENT	5
7.3	THERMAL DESIGN	5
7.4	SHOCK AND VIBRATION	5
8.0	RELIABILITY	5
8.1	DEFINITION OF A FAILURE	5
8.2	MEAN TIME TO FAILURE (MTTF)	6
8.3	MAINTAINABILITY	6
9.0	SAFETY	6
10.0	OPERATING PROFILES	6
10.1	VOLTAGE PROFILE	6
10.2	CURRENT PROFILE	7
10.3	IMPACT FORCE PROFILE	7
10.4	IMPACT FORCE vs WTT PROFILE	7
10.5	TIME TO IMPACT vs WTT PROFILE	8
10.6	DISPLACEMENT PROFILE	8
10.7	FREQUENCY RESPONSE vs WTT PROFILE	8
10.8	FREQUENCY RESPONSE vs RATED LIFE	9

## -ENGINEERING PRODUCT SPECIFICATION -95-9001

### **CENTRONICS**°

REV X2

DATE November 30, 1983

PAGE 3 OF 8

#### 1.0 GENERAL DESCRIPTION

This specification defines an 18-wire in-line stored energy dot matrix impact print head assembly. The stored energy print head is a dot matrix impact printing device for the use in the following printers.

- A. Regular high speed dot matrix printer.
- B. High resolution dot matrix printer.
- C. Graphics dot matrix printer.

### 2.0 RELATED DOCUMENTS

A. CDCC 80001003-9001 Paper Specification

B. CDCC 80002188-9001 355 Print Quality Specification

C. CDCC 80002189-9001 355Ribbon Specification

D. CDCC Engineering Standard 001

E. CDCC Engineering Standard 014

F. CDCC Engineering Standard 011

#### 3.0 PRINT HEAD CHARACTERISTICS AND PERFORMANCE

#### 3.1 PRINT HEAD CHARACTERISTICS

A. Print Wire Diameter .0138-.0140 inch B. Print Wire Column Center-to- .0301  $\pm$  .0006 inch

Center Separation
C. Print Wire Vertical Center-to- .0146 ± .0004 inch
Center Separation

D. Wire Tip Travel (Free) .025 inch min.

E. Head to Platen Gap (Head Gap Hg) .013 + .003 inch\*

F. Dynamic Print Range .006 Inch

G. Coil Resistance (In free air at 4.1 (REF) ohms

68<sup>O</sup>F room temp.)

H. Coil Inductance (in free air at .146 (REF) mH 1000 Hz)

I. Drive Voltage 36-42 volts
I. Drive Current 2.0-2.2 amp.

J. Drive Current 2.0-2.2 amp.
K. Drive Pulse Width

Single Actuator Alone 250-280 us
Individual Actuator in Print Head 300 + 20 us

L. Drive Scheme Current Limited Pulse

- \*3.1 E 1 Set up without paper or ribbon for typical 1 ply paper.

  Multi ply paper requires additional gap to maintain
  print quality and avoid smear and paper jam.
  - 2 This represents dynamic print range over which the print head performance (Section 3.2) must be maintained.

### ENGINEERING PRODUCT SPECIFICATION-

### CENTRONICS

SPEC. NO. 80002195-9001

> REV **X3**

DATE November 30, 1983

PAGE OF 8

3.2 PRINT HEAD PERFORMANCE

> Impact force and frequency response of "Single Actuator" alone and "Individual Actuator in Print Head" on one ply paper with ribbon against steel platen are specified as follows:

Α. Single Actuator

> Testing Conditions: .013 inch Head Gap

> > Pulse Form 2.0 amp x 260/270 us

> > > Strobe

Driving Voltage 36 volts min.

1. Impact Force (to be tested at

20 Hz) 0.5 Kg min.\*

2. Frequency Response 1.7 KHZ min.

Individual Actuator in Print Head В.

Testing Conditions: Head Gap .013 inch

Pulse Form 2.0 amp x 300/320 us

Strobe

Driving Voltage 36 volts min.

1. Impact Force (to be tested at

20 Hz)

0.5 Kg min.\* 1.6 KHZ min.

2. Frequency Response

Nominal variation of wire-to-wire

Flight Time in Print Head

60 us

Print Head Performance - The print head must be capable of performing to the following specifications:

Head Gap

.010-.016 inch

Driving Voltage

36-42 volts

Impact Force - Acceptable print quality darkness of 1 ply paper through 6 ply paper with ribbon.

Frequency Response

1.6 KHz min.

Ε. Rated life of each individual

actuator in head

 $500 \times 10^{6} \text{ dots}$ 

Print Head Life F.

 $250 \times 10^6$  characters

Maximum coil surface temperature for satisfied performance (with 20°C

ambient temperature

150°C

\*3.2 A1&B1 Force measurements made using 60 KHz notch filter.

PRINT HEAD OVERALL SIZE AND WEIGHT

Α. Overall Size

2.70 Dia x 3.0 L

В. Weight 350 gm (12.4 oz)

### ENGINEERING PRODUCT SPECIFICATION-

### **CENTRONICS**°

SPEC. NO. 80002195-9001

REV X2

DATE November 30, 1983

PAGE 5 OF 8

5.0 TEST EQUIPMENT OPERATION

To measure output parameters required by this specification, test the print head on the frequency and impact tester provided and maintained by test equipment engineering following approved operating and recording procedures.

6.0 SERVICE REQUIREMENTS

The stored energy print head is designed to require no service or maintenance throughout its specified life. The print head will be an operator changeable item that upon failure is replaced by a new head.

- 7.0 ENVIRONMENTAL REQUIREMENTS
- 7.1 OPERATING ENVIRONMENT

The Print Head Assembly must be capable of operating reliably per Centronics Engineering Standard 001, Class B.

7.2 STORAGE ENVIRONMENT

The Print Head Assembly must be capable of operating reliably after storage under the following conditions:

- A. Temperature/Humidity per Engineering Standard 001, Paragraph 3.2, Class B.
- B. Altitude Per Engineering Standard 001, Paragraph 4.2.
- 7.3 THERMAL DESIGN

The Print Head Assembly must operate reliably when the temperature surrounding the solenoids is 200°F (93.3°C).

7.4 SHOCK AND VIBRATION

Refer to Centronics Engineering Standard 001, Class B.

- 8.0 RELIABILITY
- 8.1 DEFINITION OF A FAILURE

A failure is any malfunction of mechanical or electrical hardware which prevents full operation of the Print Head mechanism as defined in Section 3.2D.

### ENGINEERING PRODUCT SPECIFICATION-

### **CENTRONICS**

SPEC. NO. 80002195-9001

REV X2

DATE November 30, 1983

PAGE 6 OF 8

#### 8.2 MEAN TIME TO FAILURE (MTTF)

The MTTF for the Print Head shall be independent of duty cycle. The MTTF is 500 million dots per actuator. Reliability will be tested per Centronics Engineering Standard 014 at a "B10" Life with 90% confidence.

#### 8.3 MAINTAINABILITY

Maintainability requirements are as follows:

A. Spare parts - The design must allow for availability of spare heads for a period of five (5) years from the date of sale of each mechanism.


#### 9.0 SAFETY

Print Head Assembly must meet the safety standards of Centronics Engineering Standard 011.

10.0 OPERATING PROFILES (Reference Only 10.1 Through 10.6)

The following profiles show the results of varying one or more conditions while holding the remaining conditions per Section 3. They should be used as a guide depending on driver characteristics, magnetic and tolerance conditions.

#### 10.1 VOLTAGE PROFILE



### -ENGINEERING PRODUCT SPECIFICATION-

### **CENTRONICS**°

SPEC. NO.

80002195-9001

REV DATE X2


November 30, 1983

8


PAGE

7 OF


10.2 CURRENT PROFILE



#### 10.3 IMPACT FORCE PROFILE



### 10.4 IMPACT FORCE vs WTT (WIRE TIP TRAVEL) PROFILE



### -ENGINEERING PRODUCT SPECIFICATION-

### **CENTRONICS**°

SPEC. NO.

80002195-9001

REV

X2


DATE

November 30, 1983

PAGE

8 OF 8

### 10.5 TIME TO IMPACT VS WTT PROFILE



### 10.6 FREQUENCY RESPONSE VS WTT PROFILE

